



Three-phase meter MID, calibrated - Direct kilowatt-hour meter 10A DSZ15D-3x80A MID



Eltako
 DSZ15D-3x80A MID
 28380015
 4010312501634 EAN/GTIN

10150,29 INR excl. VAT**
 plus shipping



5-6 days* (IND)

Three-phase meter MID, calibrated DSZ15D-3x80A MID meter type electronic, rated current (In) 10A, maximum current (Imax) 80A, rated voltage (Un) NL 230 ... 230V, rated voltage (Un) LL 400 ... 400V, frequency 50 ... 50Hz, accuracy class B, Polart four-wire, direct measurement version, active power energy type, suitable for purchase, two-tariff tariff version, external tariff control, backstop, calibrated, Measuring Instruments Directive approval, optical pulse output, pulse type S0, pulse rate 1000 ... 1000Imp/kWh (kvarh) , Digital display type, REG mounting type, Width in pitch units 4, Other interface design, Number of digits 7, Degree of protection (IP) IP20, Only calibrated meters are permitted for electricity billing in accordance with Section 25 of the German Calibration Act. Non-compliance is an administrative offense according to paragraph 19. Maximum current 3x80A, standby loss only 0.5 watts per path. Modular installation device for mounting on mounting rail DIN-EN 60715 TH35. 4 pitch units = 70mm wide, 58mm deep. Accuracy class B (1%). With S0 interface. The directly measuring three-phase meter measures the active energy based on the currents flowing between the inputs and outputs. The self-consumption of only a maximum of 0.5 watts effective power per path is not measured and not displayed. 1, 2 or 3 phase conductors with currents of up to 80A can be connected. The starting current is 40mA. The N connection must be present. The 7-segment LC display can be read twice within two weeks even without a power supply. The power consumption is shown on the display with a bar that flashes 100 times per kWh. Can also be used as a 2-tariff counter as standard: When 230V is applied to terminals E1/E2, a switch is made to a second tariff. To the right of the display are the MODE and SELECT buttons, which are used to scroll through the menu in accordance with the operating instructions. First, the backlight turns on. Then the total active energy per tariff, the active energy of the resettable memory RS1 or RS2 as well as the instantaneous values of power, voltage and current per phase conductor can be displayed. Error message (false): If the phase conductor is missing or the current direction is wrong, false and the corresponding phase conductor are shown on the display.

YOUR ADVANTAGES



WORLDWIDE TRADE
 Corporate video eibmarkt®



99% CUSTOMER SATISFACTION
 > 500,000 customers worldwide



DHL TRACK & TRACE
 Shipment tracking



COMPLAINTS HANDLING
 Obliging and 100% safely



25 YEARS OF EXPERIENCE
 In worldwide mail order



ORDER LIVE CHAT
 With order history



SHORT DELIVERY TIME
 Warehousing



REFUND
 Within 14 days



DATA PROTECTION
 Guarantee

© 1997-2024 eibmarkt.com GmbH - Kemmlerstrasse 1 - 08527 Plauen - Germany

eibabo® and **eibmarkt®** are registered trademarks of EIBMARKT® GmbH holding company (www.eibmarkt.de). eibabo® is a company of eibmarkt.com GmbH. eibmarkt.com GmbH is a 100% subsidiary of EIBMARKT® GmbH holding.

* Note on delivery time: Day = Monday to Friday, no public holiday in Bavaria or Saxony. Goods are also delivered on Saturdays (DHL).

** Payment methods may vary from country to country. All prices plus shipping and excluding customs duties or other additional costs (import sales tax) for deliveries outside the EU.

*** Savings compared to RRP = the manufacturer's recommended retail price. RRP is the price recommended to retailers by the manufacturer, importer or wholesaler as a resale price to the customer. The RRP is also referred to as the list price and is defined as the highest possible price that a buyer would pay for a specific product before any discounts (Source of gross list prices: Germany).

eibabo® the Smart Home technology shop
eibabo® electronics cheap online order
eibabo® electric appliances buy online

